## TENMARS ELECTRONICS CO., LTD.

6F, 586, RUI GUANG ROAD, NEIHU, TAIPEI, TAIWAN TEL : 886-2-2658-5770 FAX : 886-2-2658-5075 E-mail : service@tenmars.com



## TM-196 3 - Axis RF Field Strength Meter



TM-196 is designed for measuring and monitoring Radio Frequency(RF) electromagnetic field strength and capable of measuring the frequency range of 10Mz~8GHz. It's ideal for the applications of:

- RF power measurement for transmitters.
- High frequency(RF)electromagnetic wave field strength measurement.
- Mobile phone base station antenna radiation power density measurement.
- Spy camera, wireless bug finder.
- Wireless communication (CW, TDMA, GSM, DECT) applications.
- Wireless LAN (Wi-Fi) detection, installation.
- Cellular /Cordless phone radiation safety level.
- Microwave oven leakage detection.
- Personal living environment EMF safety.

38mv to 11v/m
3-3/4 digits maximum reading 3999
10MHz ~ 8GHz
$mV\!/m$ , $V\!/m$ , $\mu A\!/m$ , $mA\!/m$ , $\mu W\!/m2$ , $mW\!/m2$ , $\mu W\!/cm2$
0.1mV/m, 0.1µA/m, 0.001µW/m2, 0.001µW/cm2
Read storage: 200 data sets.
Adjustable threshold with ON/ OFF
Records Maximum & AVG
adjustable
2.5 times per second.
0 to 50°C (32°F to 122°F). Max. 80% RH.
9V battery(NEDA 1604 IEC 6F 22 JIS 006P)*1
approx. 5 hrs.
approx. 180g
380(L)*80(W)*77(H) mm.
Instruction manual and hard carrying case